

netlife easy system; straightforward in-house project engineering; easy installation; preset functions; simple commissioning via remote control, app, DIP switch, rotary knob, etc.

## CHARACTERISTICS

<b>Regiolux Classification</b>	netlife easy
<b>Control signal</b>	DALI
<b>Number of control gear (max)</b>	32
<b>Communication</b>	Bluetooth
<b>Sensor technology</b>	PIR - passive infrared
<b>Installation height (min/max)</b>	2m to 5m
<b>App name</b>	Osram BT Config; Osram BT Control
<b>Note</b>	up to 4 DALI sensors or DALI push button coupler can also be connected
<b>System extension</b>	easy01S
<b>Application</b>	Office, Meeting rooms, Corridors, Classrooms, Secondary rooms
<b>Function</b>	Motion detection, Corridor function, presence detection, Daylight control, Tunable white (only with DT8 luminaires), Manual dimming



## MONITORING AREA

<b>Mounting Height</b>	2,5m	3,5m	5m
<b>Ø max. sitting[S]</b>	3,3m	5m	-
<b>Ø max. radial[R]</b>	5,3m	7m	7m
<b>Ø max. tangential[T]</b>	-	-	-

